



NOTE: Effective 9/24/21, all NH and VT forward to numbers must be 11 digits

Resale Centrex USOC Guide						
Centrex Plus	Centrex Plus					Notes
Centrex Plus Class of Service 5ESS	USOC	SWITCH	ME	NH	VT	
Measured	HMHUX	5ESS		X		
Measured - FX	HNXUX	5ESS	X	X	X	
Measured - 4E	HNHUX	5ESS		X		
Unlimited	HFHUX	5ESS	X	X		
Unlimited - FX	HFXUX	5ESS	X	X		
Measured-(Non Optional) Vermont ONLY	KDJUX	5ESS			X	
Centrex Plus Class of Service DMS 100	USOC	SWITCH	ME	NH	VT	Notes
Measured	HMHJX	DMS100		X		
Measured - FX	HNXJX	DMS100	X	X	X	
Unlimited	HFHJX	DMS100	X			
Unlimited - FX	HFXJX	DMS100	X	X		
Measured-(Non Optional)	KDJJX	DMS100			X	
Centrex Plus Class of Service DMS 10	USOC	SWITCH	ME	NH	VT	Notes
Measured	HMHDX	DMS10		X		
Measured - FX	HNXDX	DMS10		X		
Measured - 4E	HNHDX	DMS10		X		
Unlimited	HFHDX	DMS10		X		
Unlimited - FX	HFXDX	DMS10		X		
Line USOCs with Centrex	USOC	SWITCH	ME	NH	VT	Notes
Primary Station Line at the Principal Location	RXR		X	X	X	
Primary Station Line OFF Premise Address Same CO	RX3		X	X	X	
Primary Station Line - Fully Restricted	RX5	DMS 10	X	X	X	
Primary Station Line - Fully Restricted Other Than Principle Location	RX6	DMS 10	X	X	X	
Extension Line TO Secretarial Answering Service Equipment - Same Exchange - Different Building	RJY		X	X	X	
Bridged Station Line - Different Address than the Primary Line in the Same CO	RVY		X	X	X	
Call Forwarding 5ESS	USOC	SWITCH	ME	NH	VT	Notes
Call Forwarding - Busy Incoming Only	E6GDF	5ESS	X	X	X	/CX 555-1234/CFW *CFBLAC FWDTON. (3-12 Digits)
Call Forwarding - Busy All Calls	E6GDF	5ESS	X	X	X	/CX 555-1234/CFBLAC FWDTON.(3-12 Digits)
Call Forwarding Does Not Answer Within Centrex	E9GDF	5ESS	X	X	X	/CX 555-1234/CFW *CFDAAC FWDTON. (2-5 Digits), TIMEOUT.18
Call Forwarding Does Not Answer All Calls	E9GDF	5ESS	X	X	X	/CX 555-1234/CFW *CFDAAC FWDTON.919145559999, TIMEOUT.18
Call Forwarding DMS 100	USOC	SWITCH	ME	NH	VT	Notes
Call Forwarding Busy Within Centrex	E6GDF	DMS100	X	X	X	/CX 555-1234/LF CFB/CFNB N X(2-5 Digits)
Call Forwarding Busy Outside Centrex	E6GDF	DMS100	X	X	X	/CX 555-1234/LF CFB, CBU/CFNB N 916179991234
Call Forwarding Does Not Answer Within Centrex	E9GDF	DMS100	X	X	X	/CX 555-1234/LF CFD/CFND N X(2-5 Digits)



Resale Centrex USOC Guide						
Call Forwarding Does Not Answer Outside Centrex	E9GDF	DMS100	X	X	X	/CX 555-1234.CFND N 96179991234/LF CFD, CDU
Call Forwarding DMS 10	USOC	SWITCH	ME	NH	VT	Notes
Call Forwarding Busy Line	E6GDF	DMS 10	X	X	X	/CX 555-1234/CFN (TN #)
Call Forwarding Does not Answer	E9GDF	DMS 10	X	X	X	/CX 555-1234/CFN (TN #)
Features	USOC	SWITCH	ME	NH	VT	Notes
Call Forwarding Variable	ESMDF		X	X	X	
Call Hold	EABDF		X	X	X	
Call Hold		5ESS	X	X	X	/MWC *MWCH1
Call Pickup Groups All Calls	E3PDF		X	X	X	
Call Pickup Groups All Lines			X	X	X	/CPG(#)
Touch-tone	7TTEX		X	X	X	
Automatic Callback (Intra-group)	SAK		X	X	X	
Call Waiting Terminating	ESXDF		X	X	X	
Call Waiting Terminating		5ESS	X	X	X	/CWTG *CWC1
Call Waiting Dial	E6C		X	X	X	
Conference Calling or Call Transfer		5ESS	X	X	X	MWC *MWCTIA1
Conference Calling or Call Transfer		DMS100	X	X	X	/LF 3WC
Directed Call Pickup (originating) with BARGE IN	DMA		X	X	X	
Directed Call Pickup (originating) without BARGE IN	E6D		X	X	X	
Directed Call Pickup (Terminating) with BARGE IN	DXA	5ESS	X	X	X	
Distinctive Ringing	BRT		X	X	X	
Speed Calling Single Digit	E6AFF		X	X	X	Switches: 5ESS & DMS100-Use 0-9
Speed Calling Two Digit	E3DFF		X	X	X	All switches-Use 20-49
Trunk Answer Any Line	TKA		X	X	X	DMS10 use 2-9
Uniform Call Distribution - Per Group	A6T	5ESS, DMS 100	X	X	X	
Features	USOC	SWITCH	ME	NH	VT	
Uniform Call Distribution - Per Line	A6V	5ESS, DMS 100	X	X	X	
Uniform Call Distribution Delay Announcement Per Arrangement	A8GCE	5ESS, DMS 100	X	X	X	
Caller ID	NXD		X	X	X	
Caller ID with Name	NLM		X	X	X	
Repeat Dialing	NX8		X	X	X	
Call Waiting ID with Name	N6W		X	X	X	
Call Trace	HLT		X	X	X	
All Call Blocking	NBJ		X	X	X	
Call Return	NX9		X	X	X	
Call ID and Call Return	NL4		X	X	X	
Call Return & Repeat Dialing	NXP		X	X	X	
Call ID, Call Return & Repeat Dialing	NL7		X	X	X	
Call Park	CP9		X	X	X	
Direct Call Park	CP8		X	X	X	
Deny usage Call Trace	HBG		X	X	X	
Deny usage *69	HBS		X	X	X	
Deny usage Busy Redial	HBQ		X	X	X	
Features	USOC	SWITCH	ME	NH	VT	Notes



Resale Centrex USOC Guide						
Anonymous Call Rejection (when Caller ID is on the Line)	AYW		X	X	X	
Anonymous Call Rejection (when Caller ID is not on the Line)	AYK		X	X	X	
Ultra Forward	FRC		X	X	X	



FairPak						Notes
Class of Service 5ESS	USOC	SWITCH	ME	NH	VT	
Measured FX	H9NUX	5ESS	X	X	X	
Measured 4E	H9EUX	5ESS		X		
Unlimited	H9FUX	5ESS	X	X		
Unlimited FX	H9GUX	5ESS		X		
Measured Non-Optional	H9OUX	5ESS			X	
Class of Service DMS 100	USOC	SWITCH	ME	NH	VT	Notes
Measured FX	H9NJX	DMS100	X	X	X	
Measured 4E	H9EJX	DMS100		X		
Unlimited	H9FJX	DMS100	X	X		
Class of Service DMS 10	USOC	SWITCH	ME	NH	VT	Notes
Measured FX	H9NDX	DMS10		X		
Measured 4E	H9EDX	DMS10		X		
Unlimited	H9FDX	DMS10		X		
Line USOCs	USOC	SWITCH	ME	NH	VT	Notes
Primary Station Line at the Principal Location	RXR		X	X	X	
Primary Station Line Off Premises Address Same CO	RX3		X	X	X	
Bridged Station Line Different Address than the Primary Line in Different CO	RVY		X	X	X	
Extension Line to TAS Equipment Same Exchange Different Building	RJY		X	X	X	
Standard Features	USOC	SWITCH	ME	NH	VT	Notes
Call Forwarding - Busy Line	E6GDF	5ESS	X	X	X	/CX/CFW *CFBLAC FWDTODN.(TN#)
Call Forwarding - Busy Line	E6GDF	DMS100	X	X	X	/CX/LF CFB, CBU/CFNB N (TN#)
Call Forwarding - Busy Line	E6GDF	DMS 10	X	X	X	/CX/CFN (TN#)
Call Forwarding Does not Answer	E9GDF	5ESS	X	X	X	/CX/CFW *CFDAAC FWDTODN. (TN#), TIMEOUT.(24
Call Forwarding Does not Answer	E9GDF	DMS100	X	X	X	/CX/LF CFD, CDU/CFND N (TN#)/RCYC 4
Call Forwarding Does not Answer	E9GDF	DMS 10	X	X	X	/CX/CFN (TN#)
Call Forwarding - Variable	ESMDF		X	X	X	
Call Hold	EABDF		X	X	X	
Call Pickup Groups (all lines)	E3PDF		X	X	X	
Call Transfer - All Calls			X	X	X	/MWC *MWCTIA1
Three Way Conference Calling			X	X	X	/MWC *MWCTIA1
Three Way Conference Calling	TWC		X	X	X	
Touch-tone ME, NH, VT	7TTEX		X	X	X	
Optional Features	USOC	SWITCH	ME	NH	VT	Notes
Automatic Callback	SAK		X	X	X	
Call Waiting Terminating (all calls)	ESXDF		X	X	X	
Directed Call Pickup (Origination) with Barge-In	DMA		X	X	X	
Directed Call Pickup (Origination) without Barge-In	E6D		X	X	X	
Directed Call Pickup (Terminating) with Barge-In	DXA	5ESS	X	X	X	
Inside/Outside Ringing	BRT		X	X	X	
Speed Calling Single Digit	D6AFF		X	X	X	All Switches, the range is 0-9
Speed Calling Two Digit	E3D		X	X	X	All Switches, the range is 20-49



FairPak						Notes
Trunk Answer Any Line	TKA		X	X	X	
Caller ID	NXD		X	X	X	
Caller ID with Name	NLM		X	X	X	
Repeat Dialing	NX8		X	X	X	
Call Waiting ID with Name	N6W		X	X	X	
Call Trace	HLT		X	X	X	
All Call Blocking	NBJ		X	X	X	
Call Return	NX9		X	X	X	
Call ID and Call Return	NL4		X	X	X	
Call Return & Repeat Dialing	NXP		X	X	X	
Call ID, Call Return & Repeat Dialing	NL7		X	X	X	
Call Park	CP9		X	X	X	
Direct Call Park	CP8		X	X	X	
Anonymous Call Rejection (when Caller ID is on the Line)	AYW		X	X	X	
Anonymous Call Rejection (when Caller ID is not on the Line)	AYK		X	X	X	
Deny usage Call Trace	HBG		X	X	X	
Deny usage *69	HBS		X	X	X	
Deny usage Busy Redial	HBQ		X	X	X	
Ultra Forward	FRC		X	X	X	